

PHOTO DETECTOR.

DATA-PEAK SWITCH:

Pressing the PEAK key again to clear the peak recording mode.

LCD DISPLAY:

3-1/2 Digits with a maximum reading of 1999.

DATA-HOLD SWITCH

pressing the HOLD key selects HOLD mode. When HOLD mode is selected, the illuminance meter stops all further measurements. Pressing the HOLD key again cancels HOLD mode, causing the illuminance meter to resume taking measurements.

POWER SWITCH:

The power switch key turns the illuminance meter ON or OFF.

LUX/FC UNIT:

Switch: pressing the Lux/FC key to choose Lux or FC unit.

BACK LIGHT BUTTON

RANGE SWITCH:

Pressing the range key changes 200Lux/20FC, 2,000Lux/200FC, 20,000Lux/2,000FC, 200,000Lux-/20,000FC ranges, circularly.



LUX	FC
200	20
2.000	200
20.000	2.000
200.000	20.000

HoldPeak® HP-881C